

# ECE 592-100 – Signal Processing Tour of Quantum Computing

Quiz 2– Spring 2023

March 6, 2023

Please remember to justify your answers carefully.

Last name: \_\_\_\_\_ First name: \_\_\_\_\_

## Question 1 (Period of signal.)

Consider the discrete time signal,  $x(n) = \cos(0.1\pi n) + \cos(0.2\pi n)$ . What is the period of this signal?

## Question 2 (Fourier using different periods.)

Consider a period discrete time signal where the period is  $N = 4$ , the samples are  $x = \{\underline{1} \ 0 \ 1 \ 0\}$ , and the underline corresponds to time index  $n = 0$ .

(a) Compute the Fourier coefficients,  $C_k$ , for  $k \in \{0, 1, 2, 3\}$ .

(b) Note that  $x$  is also periodic-2, because  $x(0) = x(2)$  and  $x(1) = x(3)$ . Using  $N = 2$ , re-compute the Fourier coefficients,  $C_k$ , for  $k \in \{0, 1\}$ .

## Question 3 (LTI systems with periodic inputs.)

Consider an input signal,  $x(n)$ , that has period  $N$ . The signal is processed by a linear time invariant (LTI) system whose impulse response is  $h$ . You will see in this question that  $y$  is also periodic with period  $N$ .

(a) Recall that we can express  $x(n)$  as a linear combination over exponential signals,

$$x(n) = \sum_{k=0}^{N-1} C_k e^{+i2\pi kn/N} = \sum_{k=0}^{N-1} C_k x_k(n),$$

where  $x_k(n) = e^{+i2\pi kn/N}$  and  $k \in \{0, \dots, N-1\}$ . Each  $x_k(n)$  can be an input to  $H$ , and corresponds to an output,  $y_k(n)$ . Express  $y_k(n)$  using  $x_k(n)$  and  $H(\omega)$ .

(b) Using linearity, what is the output,  $y(n)$ , of the LTI system for  $x(n)$ ? (Do not express your answer as convolution between  $x$  and  $h$ . Rely on part (a).)

(c) Why is your answer to part (b) periodic- $N$ ? (Its period might be smaller than  $N$  as in Question 2; but it will satisfy  $y(n) = y(n + N)$ .)